

DC to DC VOLTAGE REGULATOR/CONVERTER

This type of device is known in the electronics industry as a Buck - Boost converter

It has a fixed output voltage of 13.8 volts

**Any applied input voltage (within the specifications) above 13.8 volts will be reduced to 13.8 volts
Any applied input voltage below 13.8 volts (within the specifications) will be increased to 13.8 volts**

INSTALLATION

THIS UNIT CAN BECOME VERY WARM WITH NORMAL OPERATION

Mount the unit in an area with some natural air flow and with easy access for the wiring and mounting screws.

This unit is not waterproof.

Secure to a flat rigid surface with suitable fasteners through the holes in the base flange of the unit.

Connect the INPUT voltage to the Yellow and Black wires exiting the unit via the grommet marked 6-36 V IN.

A fuse and switch must be included in the Yellow (positive) wire.

The fuse should be correctly chosen for the appliance being operated, but should not exceed 10 amps in any case

OBSERVE CORRECT POLARITY - YELLOW INPUT WIRE IS TO POSITIVE +

Connect the OUTPUT via an appropriate connector (and optional fuse and switch) to your chosen 12 volt appliance.

OBSERVE CORRECT POLARITY - RED OUTPUT WIRE IS TO POSITIVE +

SPECIFICATIONS

Model SR138120

Input Voltage Allowable 6 to 36 volts, DC only

Output Voltage Fixed at 13.8 volts DC, $\pm 2\%$

Over-Voltage Output Protection Circuit - if circuit failure causes output voltage to rise, output voltage turned off

Maximum Output Current 10Amps

Current Limiting will occur at 10 Amps - do not use with a device attempting to draw greater than 10 Amps

Over Temperature Protection

Input/Output Isolation 500 volts

Output Voltage Ripple Factor $< .7\%$

Output and Input Short Circuit Protection

Ambient Temperature allowable from -20 to +80 degrees C (-4 to +175 F)

Standby Current (no output load) 50mA

Conversion Efficiency $\Rightarrow 85\%$

Dimensions 150 x 48 x 68 mm (6 x 1.8 x 2.6 in)

Weight 535 Grams (1.2 lb)

All specifications subject to change or design improvements without notice

WARRANTY

In the event of malfunction or failure Cruising Electronics will, at their sole discretion, either repair or replace the unit, providing that:

Malfunction has occurred within 12 months from the date of purchase

Any or all of the above listed ratings of the unit have not been exceeded

The unit has been properly and permanently installed, with correctly rated cables, fuses, switches and any other ancillary items which could reasonably be regarded as necessary to effect a safe and workmanlike installation.

The unit has not been exposed to any fluid, corrosive or hazardous substance, or excessive airborne particles

The unit is returned freight paid to Cruising Electronics or their nominated agent

Proof of purchase is provided.

DISCLAIMER

Please note that under no circumstances can Cruising Electronics be held responsible or accept liability for any consequential damages or loss whatsoever, incurred as a result of installing and/or operating this device in any situation, with or without any other device attached.

CRUISING ELECTRONICS

67 WELLINGTON STREET

RUSSELL 0202

NEW ZEALAND

TELEPHONE (09) 403735027 (027) 2552852 (+64 27 2552852)

don@cruisingelectronics.com

www.cruisingelectronics.com

